



Casambi betriebene Leuchten können direkt vom Lichtschalter gedimmt werden:



- Ohne zusätzliche Installation eines Dimmers.
- Einfach, Leuchte montieren und den bestehenden Lichtschalter als Dimmer wie nachstehend beschrieben benutzen.

Dimmvorgang:

1. Einmal schnelles Aus-/An-Schalten die Beleuchtung dimmt langsam hoch.
2. Erneutes schnelles Aus-/An-Schalten legt den Dimmwert fest.
3. Der Wert wird nun als Standard gespeichert.
4. Beim nächsten Einschalten wird der festgelegte Standard automatisch wiedergegeben.



Wichtig:

- Um den gespeicherten Standard Dimmwert wieder zu ändern, den beschriebenen Vorgang komplett ab 1.) wiederholen.
- Um 100% Helligkeit zu haben, einfach nur Punkt 1.) und nicht 2.) ausführen.




1. Gratis Casambi App aus App Store oder Google Play downloaden und installieren.
2. Schalten sie alle Casambi betriebenen Leuchten ein und starten Sie die App.



3. Leuchten mit einem Klick zu Netzwerk hinzufügen.
4. Sofort los legen! Leuchten über Smartphone und Tablet schalten*

Mehr Infos benötigt?
Nutzen sie unser Fragezeichen




Bei Leuchten mit Umschaltmodul sind folgende Einstellungen vorzunehmen:

- Netzwerk öffnen, „bearbeiten“ auswählen und die gewünschte Leuchte selektieren. „Smarter Schalter“ von Einstellung „Dimmen und Speichern“ auf „Nicht in Benutzung“ umstellen.
- Den „Start Zustand“ auf „Standard Modus“ belassen.
- Die Funktion „Modi“ bleibt im Standardmodus. Der „Zustand“ des Dimmers muss größer als 50 % sein.

*Info: ab iPhone 4S, iPad mini, iPad der 3. Generation und iPod touch der 5. Generation. Min. Android 4.4.2 Kikat mit Bluetooth 4.0 oder neuere Generation. Empfohlen Android 5.0


Casambi embedded lights can be dimmed directly from the wall switch:



- Without an installation of an additional dimmer.
- Just plug in your lamp and use the existing wall switch as your dimmer.

Dimming process

1. Turn lights on from a wall switch.
2. Make a flick by quickly turning wall switch off (max 1 sec.) and back on. The light level starts to increase gradually.
3. Make another flick at desired dim level. The selected level is saved automatically.




Important:

- To change the adjusted brightness level start dimming process from the beginning.
- If the second flick is not done in 8 sec. The light intensity reaches its maximum level..

1. Download and install Casambi App from App Store or Google Play.
2. Open Casambi App when all our Casambi embedded lamps are switch on.



3. One click adds all your lamps to a new network.
4. That's it! Control all your lamps with your smartphone or tablet*



Need more information? Try our question mark.



Do the following setting for luminaires with switch module:

- open network, choose "edit" and select the luminaire desired. Change "Smart Switching" under "Dim and save" to "Not in use".

- Keep „Startup State“ at "Default mode"

- function "Modes" remains in default mode. The dimmer "state" must be more than 50 % .

*compatible since iPhone 4S, iPad mini, iPad of the 3rd generation and iPod touch of the 5th generation. Android up to 4.4.2 Kitkat with Bluetooth 4.0Empfohlen Android 5.0